



696 Winsted Road • Torrington, Connecticut 06790

www.experimentalc.com

Mon.-Fri 8am-5pm Sat. 7:30am-5pm Sun. 7:30am-Noon

RETURNS DURING STORE HOURS ONLY!!

(860) 496-RENT (7368) (Phone) • (860) 618-5600 (Fax)

OPERATING AND SAFETY INSTRUCTION SHEET FOR POPCORN MACHINE

WARNING: BEWARE OF HOT SURFACES ON KETTLE AND SURROUNDING SURFACES TO AVOID BURNS

★ ★ FOR ADULT USE ONLY ★ ★

PLEASE EXERCISE SOUND JUDGEMENT AND COMMON SENSE WHEN OPERATING THIS MACHINE. KEEP ALL BYSTANDERS OUT OF THE WORK AREA. OPERATOR NEEDS TO WEAR SAFETY GLASSES.

Set-Up:

Plug machine into a 20 amp 120 volt isolated outlet (an outlet where nothing else is running off the circuit).

If possible, plug unit directly into outlet.

Any extension cord must be marked/rated 10 gauge, AND BE NO LONGER THAN 25'.

Place unit on a steady, solid surface and out of the way of guest traffic.

Operation:

1. Turn kettle switch and kettle motor "ON"
2. Allow kettle to heat for 4 minutes ONLY
3. For best results, use a Gold Medal MEGA POP 10.5 ounce popcorn kit.
4. Cut oil package along top edge and squeeze in oil first, allowing it to melt before adding the corn and salt into the kettle. Close the lid.
5. After the corn has stopped popping, rotate the handle to empty the kettle. There is a stop to prevent the kettle from being rotated too far. Return the kettle to the upright position.
6. Repeat the cycle starting with step #3.

For Best Results

Always pop 4-5 batches in a row. The quality and flavor are better on batch two through five.

The kettle's gear (up on top) must be fully engaged with the motor drive gear during popping operation. Your popcorn will burn if it is not.

TRANSPORT SECURELY. THE KETTLE MUST BE REMOVED AND THE POPCORN MACHINE TIED IN AND SECURED IN THE VEHICLE. YOU ARE RESPONSIBLE FOR BROKEN PLEXIGLASS.

One (1) 10.6 ounce Popcorn Kit will make 15 - 1oz servings using #3 (1oz) bags.

All local health department regulations should be observed.